

Cisco ATA 186 (H323) Configuration to use SIP Micro's H323 VoIP Account

UIPassword:		UseTftp:	0
TftpURL:	0	CfgInterval:	3600
EncryptKey:		EncryptKeyEx:	00000000000000000000
Dhcp:	0	StaticIP:	192.168.0.1
StaticRoute:	192.168.0.254	StaticNetMask:	255.255.255.0
UID0:	E.164	PWD0:	H.323 ID
UID1:	E.164	PWD1:	H.323 ID
GkOrProxy:	SIPMICRO'S 1st GK	Gateway:	0
UseLoginID:	1	LoginID0:	H.323 ID
LoginID1:	H.323 ID	AltGk:	SIPMICRO'S 2nd GK
AltGkTimeOut:	0	GkTimeToLive:	300
GkId:	.	MediaPort:	16384
LBRCodec:	0	AudioMode:	0x00150015
RxCodec:	0	TxCodec:	0
NumTxFrames:	2	CallFeatures:	0x00000002
PaidFeatures:	0x00000002	CallerIdMethod:	0x00019e60
FeatureTimer:	0x00000000	FeatureTimer2:	0x0000001e
Polarity:	0x00000001	ConnectMode:	0x0008c4cb
AutMethod:	0x00000000	TimeZone:	17
NTPIP:	0.0.0.0	AltNTPIP:	0.0.0.0
DNS1IP:	DNS Server IP	DNS2IP:	DNS Server IP
TOS:	0x000068b8	SigTimer:	0x01418564
OpFlags:	0x00000002	VLANSetting:	0x0000002b
FXSInputLevel:	-1	FXSOutputLevel:	-4
NPrintf:	0.0.0.0.0	TraceFlags:	0x00000000
SyslogIP:	0.0.0.0.514	SyslogCtrl:	0x00000000
RingOnOffTime:	2,4,25	IPDialPlan:	1
DialPlan:	0	DialPlanEx:	0
DialTone:	2,31538,30831,1380,1	BusyTone:	2,30467,28959,1191,15
ReorderTone:	2,30467,28959,1191,15	RingBackTone:	2,30831,30467,1943,2
CallWaitTone:	1,30831,0,5493,0,0,240	AlertTone:	1,30467,0,5970,0,0,480
CallCmd:	Af;AH;BS;NA;CS;NA;D	CFGID:	0x00000000