

WellTech FXS Configuration to use SIP Micro's H323 VoIP Account

H323 Configuration	
Mode:	<input checked="" type="radio"/> GK routed <input type="radio"/> Peer-to-Peer
Gatekeeper IP Address:	<input style="color: red;" type="text" value="Gatekeeper DNS or IP"/>
2nd Gatekeeper IP:	<input type="text" value="0.0.0.0"/>
Gateway Type:	<input checked="" type="radio"/> Gateway <input type="radio"/> Terminal
Registered Prefix:	<input style="color: red;" type="text" value="E.164"/>
Line1 Number:	<input style="color: red;" type="text" value="E.164"/>
Line2 Number:	<input style="color: red;" type="text" value="E.164"/>
Registered Alias:	<input style="color: red;" type="text" value="H.323ID"/>
Display Information:	<input type="text" value="2FXS"/>
Multicast:	<input type="radio"/> enable <input checked="" type="radio"/> disable
RTP Port:	<input type="text" value="16384"/>
Time To Live (TTL):	<input type="text" value="60"/>
Gatekeeper finding port:	<input type="text" value="1718"/>
Gatekeeper RAS Port:	<input type="text" value="1719"/>
H225 RAS Port:	<input type="text" value="1024"/>
H225 Call Signal Port:	<input type="text" value="1720"/>
Response Timeout:	<input type="text" value="15"/>
Connection Timeout:	<input type="text" value="200"/>
<input type="button" value="OK"/>	

System Configuration	
Keypad Type:	<input type="radio"/> In-Band <input type="radio"/> H.245(Alpha) <input type="radio"/> H.245(Sig) <input type="radio"/> Q.931 <input checked="" type="radio"/> RFC2833
Dial Plan:	<input type="text" value="0"/>
Inter Digit Time:	<input type="text" value="3"/>
Busy Forward:	<input checked="" type="radio"/> ON <input type="radio"/> OFF
Gateway Service:	<input checked="" type="radio"/> Normal <input type="radio"/> Hotline
Call Alive:	<input type="radio"/> ON <input checked="" type="radio"/> OFF
Prefix:	<input type="text"/>
Prefix Switch:	<input type="radio"/> ON <input checked="" type="radio"/> OFF
Prefix Disable Digit:	<input type="text" value="*"/>
<input type="button" value="OK"/>	

Voice Configuration					
Codec	1st	2nd	3rd	4th	5th
Priority	G.723.1	G.729	G.729a	G.729b	G.729ab
Frame Size	G.723 30ms	G.729 20ms	G.729a 20ms	G.711u 20ms	G.711a 20ms
G723 Silence Suppression:	<input type="radio"/> enable <input checked="" type="radio"/> disable				
Volume:	voice 28	input 28	DTMF 23		
Echo Canceller:	<input checked="" type="radio"/> enable <input type="radio"/> disable				
Jitter Buffer:	Min. Delay 90			Max. Delay 150	
Optimized Factor (Jitter):	9				
OK					

Support Configuration	
T.38 FAX:	<input checked="" type="radio"/> enable <input type="radio"/> disable
T.38 FAX ECM:	<input checked="" type="radio"/> enable <input type="radio"/> disable
Fast Start:	<input checked="" type="radio"/> enable <input type="radio"/> disable
H.245 Tunneling:	<input checked="" type="radio"/> enable <input type="radio"/> disable
H.245 Message After Fast Start:	<input checked="" type="radio"/> enable <input type="radio"/> disable
OK	